



# Installation instructions for the Leica Q2

## Firmware 1.1

Dear Customers,

Installing the firmware 1.1 on your Leica Q2 will add additional functions and improve performance to your camera.

### Update Contents

Model Number	LEICA Q2
Update Version	1.1
Update Filename	Q2__11_.lfu

### Overview

Version	Description
Version 1.1	<ul style="list-style-type: none"><li>• <b>DNG files recording</b> DNG files recorded in 'Continuous Super Speed' mode are now readable in Adobe products.</li><li>• <b>Burst Shooting Mode + attached flash</b> In 'Burst Shooting Mode' (H/M/L) the attached flash is now triggered more than once (depending on the power of the flash).</li><li>• <b>Download of images via Leica FOTOS</b> Stabilized image download via Leica FOTOS in combination with 'Remote-Wake up' as well as display of aperture values after wake up.</li><li>• <b>Interval shooting in Drive Mode</b> - In 'JPG´s only' setting now images can be taken with 1s 'Interval' continuously without losing frames. Also the performance with 'DNG + JPG' has been improved.</li></ul>

\_ REMARK: Due to general SD-card writing time please use an interval time of longer than 2 sec. in order to secure that all images (DNG + JPEG) will be saved.

**Please follow these steps to install the new firmware for your Leica Q2 camera:**

Recharge the battery to 100% and insert the battery into the camera.

1. Download the new firmware file to your computer.
2. Prepare the SD card for installation:
  - a. Please make sure that the card contains at least 200 MB of free disk space.
  - b. It is recommended to format the card inside the camera before continuing.
  - c. Download the new firmware file to your computer.
  - d. Copy the firmware file to the root directory of the SD card.
  - e. Eject the SD card properly from your computer.
3. Insert the SD card into the camera and switch the camera on.
4. Go to Main Menu / Camera Information / Camera Firmware
5. Press “Yes” to confirm and start the process;
  - a. You should save your current profiles to the SD card before proceeding with the update.
  - b. Wait until the update installation is completed.
  - c. Restart the camera; do not eject the SD card.
  - d. Please load your last saved profiles from the SD card after the first startup.
6. The update process is complete.

**CAUTION:**

Please do **NOT** turn off your camera, remove the Battery, or remove the SD Memory Card while the update is running.

**DISREGARDING THIS WARNING CAN CAUSE SERIOUS DAMAGE TO YOUR CAMERA!**